

AP 142								
COLOUR	TYPE	WIDTH	LENGTH	DIAMETER	CONDUCTOR	WALL OF COPPER	TERMINAL	UNITS
RED	RING TERMINAL	4.8mm	30mm	9.5mm	0.5-1.0mm <sup>2</sup> (AWG22-18)	0.7mm		7
RED	RING TERMINAL	4.8mm	33mm	11.6mm	0.5-1.0mm <sup>2</sup> (AWG22-18)	0.7mm		7
BLUE	RING TERMINAL	5.8mm	33mm	12mm	1.5-2.5mm <sup>2</sup> (AWG16-14)	0.8mm		7
BLUE	RING TERMINAL	5.8mm	35mm	12mm	1.5-2.5mm <sup>2</sup> (AWG16-14)	0.8mm		7
YELLOW	RING TERMINAL	6.8mm	37mm	12mm	3.0-6.0mm <sup>2</sup> (AWG12-10)	1.0mm		7
YELLOW	RING TERMINAL	6.8mm	39mm	15mm	3.0-6.0mm <sup>2</sup> (AWG12-10)	1.0mm		7
RED	TAB TERMINAL	4.8mm	28mm	21mm	0.5-1.0mm <sup>2</sup> (AWG22-18)	0.4mm		10
BLUE	TAB TERMINAL	5.8mm	28mm	21mm	1.5-2.5mm <sup>2</sup> (AWG16-14)	0.4mm		10
RED	PUSH ON FULLY INSULATED TERMINAL	6.2mm	30mm	6.6mm	0.5-1.0mm <sup>2</sup> (AWG22-18)	0.4mm		10
BLUE	PUSH ON FULLY INSULATED TERMINAL	6.2mm	30mm	6.6mm	1.5-2.5mm <sup>2</sup> (AWG16-14)	0.4mm		10
RED	SHRINK BUTT CONNECTOR	4.8mm	35mm	1.6mm	0.5-1.0mm <sup>2</sup> (AWG22-18)			20
BLUE	SHRINK BUTT CONNECTOR	5.8mm	35mm	2.2mm	1.5-2.5mm <sup>2</sup> (AWG16-14)			20
YELLOW	SHRINK BUTT CONNECTOR	6.8mm	41mm	3.4mm	4.0-6.0mm <sup>2</sup> (AWG12-10)			20